



SMART GATEWAY

USER GUIDE

ZIGBEE




Product Configuration



01

Packaging accessories



02

Feature & Specifications

Support Zigbee 3.0 protocol to add Zigbee subsystem
 App remote control
 USB power: 5V/1A
 USB power supply: 5V/1A
 Wireless protocol: Zigbee IEEE 802.15.4
 Communication Protocol: Zigbee 3.0
 Frequency band: 2.4 ~ 2.485GHz
 Standby power: 0.5W
 Max. output power: 19dBm
 Cable interface: RJ45 10/100M ethernet port
 Firmware upgrade: Support OTA
 Number of sub-devices that can be added: 128
 Working temperature: 0 ~ 55°C
 Working humidity: 10% ~ 90%RH
 Storage temperature: -10 ~ 60°C
 Storage humidity: 10 ~ 90%RH
 Product size: 78mm x 78mm x 25mm


03

LED State

Device Status	LED State
Standby state	Blue and purple on
The network connection has been configured	Blue is steady on and the purple is off
Add sub-devices	Steady blue and flashing purple
Data transmission	Purple is off and flashing blue
Reset	Long press the reset button for 7s

Install and Use

- 1. Installation procedure:**
- Open the product package
 - Connect the gateway to the power supply and connect the router through the network cable
 - Add the device after it is started



2. Matters needing attention:

- The network cable must be connected to the Lan port of the router, and the Wan port cannot be used
- Ensure that the phone and gateway are on the same LAN during the adding process
- SmartLife and HomeAPP cannot be used together

05


Add Home APP

- Note:**
- Before use, ensure that the network cable is connected and the gateway is powered on normally
 - When adding a gateway, the phone must be on the same LAN as the gateway
 - Before adding the gateway, make sure that the gateway is in the unconfigured state (blue and purple dual lights are on). In the unconfigured state, long press the reset button for 7 seconds before adding the gateway
 - When the Home hub is not set, Home only supports the use of LAN, and the gateway will not exit the state of network distribution after being added through Home

06

Download the App


- Open "APP Store", search "HomeKit" and download the APP
- After downloading, open the APP and log in with your iCloud account



07


Add Gateway

- Open Home APP, go to the add page




08

- Scan QR code to add; After entering the add interface, scan the QR code at the bottom of the gateway directly



09

- Manually enter the ID to add



10

Add and manage sub-devices

1.Sub-device additions

- Long press the reset button of sub-device to make the sub-device enter the standby state (the indicator lights on).
- Short press the gateway reset button to make the gateway enter the sub-device adding state (steady blue, flashing purple).
- Devices will be automatically added to the gateway. After the addition, the icon of sub-devices will appear in the APP (sub-devices will be in the room of the gateway by default after being added)

11

2. Sub-device settings

- Modify room location: Long press the sub-device icon to enter Settings



12

- Enable/disable APP push



13

- Delete sub-device: delete sub-device need to go through the TUYA APP. Please refer to the instructions in the TUYA section

Setting up home hub

- (The instructions take Apple TV as an example. For details, please refer to the official website of Apple)
- Note:**
- Make sure that the Apple TV is powered on and connected to the network cable before adding it
 - Ensure that the phone is on the same LAN as the Apple TV
 - The Apple TV login account must be the same as the iPhone login account

14

1.Log in account



15

2.Connect the Home APP



16




3.Set up the room and open home hub



18

4.The addition is complete and can be used by the external network



19

Family share

- Note:** Need to set up the home hub after the share account can access the external network



20


Get Started with Tuya App

- 1. Download APP**
Download the "Smart life" app from APP Store or Google Play to your mobile.



- 2. Register and Login**
A. Launch the "Smart life" app.
B. To register, enter your mobile phone number or email address, create a password, then login to the app.
C. Login if you have an account already.

21




22

Use of Gateway


1.Add Gateway

- Method 1:** APP LAN automatically searches and adds devices. When the phone is connected to Wi-Fi, open the APP and add devices, the APP will automatically search gateways in the LAN




23

Method 2:APP LAN search and add




24

2.Add sub-devices, access the gateway page to add sub-devices




25

3.Delete sub-devices. Select the sub-device that you want to delete, the sub-devices settings page is displayed



26

4.Delete the gateway




27


Other functions

1.Shared device

- Single device sharing




28




29

(2) Family group sharing




30

2.Product linkage



31


2.Product linkage



32

3.Management of push

- All APP push: If push is closed here, all devices in the APP will not receive push, but message recording will not be affected



33

3.0

Smart Home Device contains WiFi smart device, Z-Wave device and ZigBee device, give you more choices to create a new smart life.

Wide application on the living room, kitchen, bedroom, bathroom, garage, garden, yard or basement of your home, office, warehouse, chain store...

Make life smarter and more convenient.

34



Use of the Works with Apple badge means that an accessory has been designed to workspecifically with the technology identified in the badge and has been certified by the developer to meet Apple performance standards. Apple is not responsible for the operation of this device or its compliance with safety and regulatory standards.

