


SP637E Instructions



SP637E SPI CCT LED Controller



1.Brief:

SPI dual channel addressable CCT LED controller, controlling 2 channels of single-wire RZ LED driver IC to achieve static dimming, dynamic effects, music effects.

2.Features:

1. Support App control, 2.4G touch remote control and 2.4G touch 86-type control panel;
2. Support up to 600 single-wire RZ RGB LED driver ICs;
3. Built-in a variety of CCT dynamic effects and music effects, with multiple adjustable parameters;
4. Capture music through the phone microphone, player streamer and on-board microphone;
5. Support effect collection;
6. With a variety of ON/OFF animation effects;
7. With ON/OFF timer function;
8. Support OTA firmware upgrade.

3.APP:



- 1.SP637E supports App control for iOS and Android devices.
- 2.Apple devices require iOS 10.0 or higher, and Android devices require Android 4.4 or higher.
- 3.You can search “BanlanX” in App Store or Google Play to find the APP, or scan the QR code to download and install

Operations

- Open the App, click the + icon in the top right corner of the home page to add device;
- Click the ⚙ icon in the upper right corner of the App to enter the settings page, where you can modify the device name, set the timings, set the on/off effect, OTA firmware upgrade, etc.

4.Work With 2.4G Touch Remote Control:

The 2.4G touch remote control models (RB2 and RC2) matched with SP637E are as follows:

- Support one-to-many control, one remote control can control multiple controllers.
- Support many-to-one control, each controller can bind up to 5 remote controls.
- Support unified control and 4-zones control.

NOTE: For more information, refer to "2.4G Touch Remote Control Instructions"



RB2



RC2

(Requires separate purchase)

5. Technical Parameters:

Working Voltage: DC5V~24V	Working Current: 1mA~10mA
Working Temp: -20°C~60°C	Dimension: 78mm*56mm*20mm

6. Wiring

