BASIC DESCRIPTION

Easy stair lighting controller

Stair Controller Dimension



Product Parameters

Product Name	Easy stair lighting controller
Model Number	RL-S01
Input Voltage	DC12V-DC24V
Max Current	8A
Power	DC12V/96W Max, DC24V/192W Max
Material	PC
Color	White

Installation Diagram



2pcs
Sensor cable length: 1m



1pcs
Extension cord length: 5m

How to use

Step number

Easy series stair lighting controller work with main cable. If your stair have 16 steps, then use 16 steps main cable. If your stair have 20 steps, then use 20 steps main cable.

Delay time

Touch "+" and "-" to adjust delay time

20 seconds delay time	Blue signal light blink 2 times quickly
40 seconds	Blue signal light blink 3 time quickly
60 seconds	Blue signal light blink 4 time quickly
120 seconds	Blue signal light blink 5 time quickly
180 seconds	Blue signal light blink 6 time quickly
300 seconds	Blue signal light blink 7 time quickly

Tuya Control

Use Tuya app to control the brightness

A. Download Tuya app

B. Scan device

C.Adjust brightness

D. Timer
We can set the time to turn on or turn off the stair lighting

Product Details



Application